

# CENTENNIAL BRASS – LANDSCAPE LIGHTING

---

- Centennial Brass presents a natural vintage look and feel with brown and gold undertones that will patina over time
- Durable solid cast brass construction
- Create your ideal lighting layout with Accent, Path, Deck, Wall-Wash and In-Ground fixtures
- Optimized to work with Kichler LED retrofit lamps



**15470CBR**  
6" Dome Path Light



**15478CBR**  
Path Light



**15480CBR**  
Missionary Path Light



**15475CBR**  
Accent Light



**15384CBR**  
Accent Light



**15481CBR**  
In-Ground with  
Frosted Lens



**15482**  
In-Ground Rock Guard  
with Clear Lens



**15477CBR**  
Deck Light



**15476CBR**  
Wall Wash Clear Lens with  
Frosted & Linear Lens Options

See our line of LED Lamps at  
[Kichler.com/Landscape](http://Kichler.com/Landscape)



**KICHLER**



Ordering Guide & Finish	15470 CBR	15478 CBR	15480 CBR	15475 CBR	15384 CBR
Housing	Cast Brass	Cast Brass	Cast Brass	Cast Brass	Cast Brass
Lamp Base	12V T5 wedge base socket	12V bi-pin, high temperature porcelain socket	12V bi-pin, high temperature porcelain socket	12V bi-pin, high temperature porcelain socket	12V bi-pin, high temperature porcelain socket
Supplied Lamp	16.25-W(VA) 921X (17025). Xenon light source. Power usage at 12V AC input. VA MAX: 16.25-W(VA).	Lamp not supplied unless noted	Lamp not supplied unless noted	Lamp not supplied unless noted	Lamp not supplied unless noted
Incandescent Lamp Options	11.6-W(VA) 912X (17023) 6.5-W(VA) 918X (17022) 4-W(VA) 901X (17021)	12V AC input Max: 20W(VA) T-3	12V AC input Max: 20W(VA) T-3	12V AC/DC input Max: 35-W(VA) MR-16	Power usage at 12V AC input VA Max: 50-W(VA) MR-16 35-W(VA) Max on 15384CO 20-W(VA) Max Canada
LED Lamp Options	2W (18039-18041) Compares up to 16W Xenon	2W G4/T3 Bi-Pin (18042-18044) Compares up to 20W Halogen	2W G4/T3 Bi-Pin (18042-18044) Compares up to 20W Halogen	4W (18126-18133) Compares up to 20W Halogen 5W (18134-18141) Compares to 35W Halogen	4W (18128-18133) Compares up to 20W Halogen 5W (18134-18141) Compares to 35W Halogen
Wiring	24" of usable #18-2, SPT-1-W leads. Cable connector supplied.	30" of usable #18-2, SPT-1-W leads. Cable connectors not included.	30" of usable #18-2, SPT-1-W leads. Cable connectors not included.	30" of usable #18-2, SPT-1-W leads.	35" of usable #18-2, SPT-1-W leads. Cable connector supplied.
Mounting Accessories	8" In-ground slotted stake (Included)	8" in-ground stake (Included)	8" in-ground stake (Included)	8" in-ground stake (Included)	8" In-ground slotted stake (Included)
Optional Mounting Accessories	15601 – Surface Mounting Flange, 15607 – Surface Mounting Bracket	N/A	N/A	15601 – Surface Mounting Flange 15607 – Surface Mounting Bracket 15609 – Junction Box Mounting Bracket 15647 – 90° Elbow 15649 – Stem Coupler 15645, 15656, 15657, 15658 or 15570 – Stems, LK87CBR	15601 – Surface Mounting Flange 15607 – Surface Mounting Bracket 15609 – Junction Box Mounting Bracket 15647 – 90° Elbow 15649 – Stem Coupler 15645, 15656, 15657, 15658 or 15570 – Stems
Optional Lens Accessories	N/A	N/A	N/A	N/A	15675 LIN – Linear Lens 15676 FRO – Frosted Lens 15679 BK – Hexcell Louver Shield 15686 BL – Blue Filter
Notes	Coordinates with our 15310 & 15410 Domed Roof series. Brass will naturally patina over time.	Optimized for LED fit & lamp performance. Brass will naturally patina over time.	Optimized for LED fit & lamp performance. Brass will naturally patina over time.	Not recommended for down light applications. Optimized for LED fit & lamp performance. Brass will naturally patina over time.	Not recommended for down light applications. Optimized for LED fit & lamp performance. Brass will naturally patina over time.



Ordering Guide & Finish	15481 CBR	15482 CBR	15477 CBR	15476 CBR
Housing	Cast Brass with heat resistant frosted lens	Cast Brass Rock guard with clear lens	Cast Brass	Cast Brass with clear lens
Lamp Base	12V bi-pin, high temperature porcelain socket	12V bi-pin, high temperature porcelain socket	12V T5 wedge base socket	12V T5 wedge base socket
Supplied Lamp	Lamp not supplied unless noted	Lamp not supplied unless noted	Lamp not supplied unless noted	Lamp not supplied unless noted
Incandescent Lamp Options	12V AC input. Max: 20-W(VA) MR-16	N/A	12V AC/DC input Max: 13W (VA) Type 912	Power usages at 12V AC input Max: 17-W(VA) Type 921
LED Lamp Options	4W (18126-18133). Compares up to 20W Halogen. 5W (18134-18141). Compares to 35W Halogen.	N/A	2W T5 Side mount wedge base (18120-18121). Compares up to 16W Xenon.	2W T5 Side Mount Wedge Base (18120-18121). Compares up to 16W Xenon.
Wiring	34" of usable #18-2, SPT-1-W leads. Cable connectors not included.	34" of usable #18-2, SPT-1-W leads. Cable connectors not included.	73" of usable #18-2, SPT-1-W leads. Cable connectors not included.	53" of usable #18-2, SPT-1-W leads. Cable connectors not included.
Mounting Accessories	N/A	N/A	Mounting hardware included 2 #8 screws (Included)	8" in-ground stake (Included)
Optional Mounting Accessories	N/A	N/A	N/A	15601 – Surface Mounting Flange 15607 – Surface Mounting Bracket 15609 – Junction Box Mounting Bracket 15647 – 90° Elbow 15649 – Stem Coupler 15645, 15656, 15657, 15658 or 15570 – Stems, LK87CBR
Optional Lens Accessories	15782 Rock guard with clear glass	N/A	N/A	Optional Lens Accessories Supplied: Linear and Frosted Lens Options.
Notes	Composite installation sleeve included. Optimized for LED fit & lamp performance. Brass will naturally patina over time.	Brass will naturally patina over time.	Optimized for LED fit & lamp performance. Brass will naturally patina over time.	Optimized for LED fit & lamp performance. Brass will naturally patina over time.